

140 COMMERCE DRIVE MONTGOMERYVILLE, PA 18936-1013


PHONE: (215) 631-9840 FAX: (215) 631-9855

#### MS1406

# RF & MICROWAVE TRANSISTORS FM MOBILE APPLICATIONS


#### **Features**

- 175MHz
- 12.5 VOLTS
- GOLD METALIZATION
- Pout = 20WATTS
- Gp = 8.0 dB MINIMUM
- COMMON EMITTER CONFIGURATION



#### **DESCRIPTION:**

The MS1406 is a silicon NPN transistor designed for 12.5V AM Class C amplifiers operating in the 118–136 MHz aviation band and for 28V FM Class C amplifiers used in ground station transmitters. Diffused emitter ballast and gold metalization provide maximum ruggedness and reliability.



## ABSOLUTE MAXIMUM RATINGS (Tcase = 25°C)

Symbol	Parameter	Value	Unit
$V_{CBO}$	Collector- Base Voltage	65	V
V <sub>CEO</sub>	Collector-Emitter Voltage	35	V
V <sub>EBO</sub>	Emitter-Base Voltage	4.0	V
Ic	Continuous Collector Current	3.0	Α
P <sub>D</sub>	Total Dissipation	30	W
Tj	Junction Temperature	200	°C
T <sub>STG</sub>	Storage Temperature	-65 to +200	°C

#### **Thermal Data**

R <sub>TH(J-C)</sub>	Thermal Resistance Junction-case	5.8	°C/W
----------------------	----------------------------------	-----	------





# **ELECTRICAL SPECIFICATIONS (Tcase = 25°C) STATIC**

Symbol	Test Conditions		Value			
Syllibol	rest conditions		Min.	Typ.	Max.	Unit
BV <sub>CES</sub>	I <sub>C</sub> = 200 mA	V <sub>BE</sub> = 0 mA	65			V
BV <sub>CEO</sub>	$I_{C} = 200 \text{ mA}$	$I_B = 0 \text{ mA}$	35			V
BV <sub>EBO</sub>	I <sub>E</sub> = 10 mA	I <sub>C</sub> = 0 mA	4.0			V
I <sub>CBO</sub>	V <sub>CB</sub> = 30 V	$I_E = 0 \text{ mA}$			1.0	mA
h <sub>FE</sub>	V <sub>CE</sub> = 5 V	I <sub>C</sub> = 200 mA	10		200	

#### **DYNAMIC**

Symbol	Test Conditions			Value			
Symbol		rest conditions			Typ.	Max.	Unit
P <sub>out</sub>	f = 175MHz	$P_{IN} = 3.0W$	$V_{\text{CE}} = 28V$	20			w
G <sub>P</sub>	f = 175MHz	$P_{\text{IN}} = 3.0W$	$V_{\text{CE}} = 28V$	8.2			dB
ης	f = 175MHz	$P_{\text{IN}} = 3.0W$	$V_{\text{CE}} = 28V$	60			%
Сов	V <sub>CB</sub> = 30V	f = 1 MHz				35	pf

### **IMPEDANCE DATA**


FREQ	$Z_{IN}\!(\Omega)$	$Z_{\mathtt{CL}}\!(\Omega)$	
175 MHz	1.1 + j1.15	9.0 - j9.60	

 $\overline{P_{IN} = 3.0W}$   $V_{CC} = 28V$ 





#### PACKAGE MECHANICAL DATA



	MINIMUM INCHES/MM	MAXIMUM INCHES/MM		MINIMUM INCHES/MM	MAXIMUM INCHES/MM
Α	.220/5,59	.230/5,84	1	.155/3,94	.175/4,45
В	.980/24,89		J		.750/19,05
С	.370/9,40	.385/9,78			
D	.004/0,10	.007/0,18			
E	.320/8,13	.330/8,38			
F	.100/2,54	.130/3,30			
G	.450/11,43	.490/12,45			
Н	.090/2,29	.100/2,54			